

## Somfy LT30



The Somfy LT30 Shade Motor is a battery operated motor. The Somfy LT30 motor can be configured for use with 1.5" tubes or 1.25" tubes. The Somfy LT30 RTS Round Head Motor is controlled via Somfy's RTS RF technology which offers the user single or group control as well as X10, Timer, RS232 Control etc. This is a simple, easy to use and easy to install solution for your shade motorization needs. This motor can be powered via 12VDC batteries as well as wall plug-in transformer.

The Somfy LT30 Shade motors can be used to retrofit your existing Chain/Clutch shades.

The Somfy LT30 motor stores the limits set by the remote controls and memory is not lost when power is disconnected. With the momentary press of a button, you can command the shade to go Full Up, Full Down and a customer specified preferred position. No need to hold the button down and wait for the shade to reach the desired position.

### Somfy LT30 RTS 12V Shade Motor Specifications:

- Operating Voltage: 12VDC
- Max Current Draw: 1.0A
- Torque: 1.1Nm
- Motor Speed: 27 RPM
- Lift Capacity - Not including Tube Weight
  - 1.25" Tube: 9.68lb
  - 1.5" Tube: 8.07lb
  - 2" Tube: 6.05lb
- Standard RTS RF Control Only
- Compatible with Somfy RTS RF Control Technology
- Warranty 5 years
- Power Supply Options:
  - LT30 Connector w/ 10' Leads Only - No Power Supply or Battery Holder
  - 12VD100W - White 12VDC 1Amp Wall Plug Power Supply - No LT30 Connector
  - Reloadable Battery Wand - (Requires 8 Lithium AA Batteries NOT Included)
  - Reloadable Battery Wand with Set of 8 Energizer Lithium AA Batteries
- Dimensions
  - Overall: 10.5" L x 1.75" W x 3.5" H
  - Tube insertion length: 10.625"
- Weight: App. 9oz (.55 lb)